

Maxitone Conventional Sounder & Combined Sounder/Flasher (ZMT/8R, ZMT/8W & ZMTF/8R)



ZMT/8W

The Maxitone sounder is an ideal alternative to fire bells and for external use. It is housed in an attractive horn comprises of flame retardant ABS. Eight selectable tones and volume control are featured to meet most requirements.

The Maxitone is also available with transparent polycarbonate front which will provide both visual and audible alarm.



ZMT/8R

Features

- ✓ High output
- ✓ 8 selectable tones
- ✓ Volume control



ZMTF/8R

Model	ZMT/8R	ZMT/8W	ZMTF/8R
Part No.	42-001	42-001A	42-032
Sound Output	See current consumption table		
Colour	Red	White	Red
Operating Voltage	17-35V DC		
Quiescent Current	0mA		
Alarm Current @ 24V	See current consumption table		
Operating Temperature	-20°C to 60°C		
Minimum Continuous Temperature	0°C		
Maximum Humidity	95% RH non condensing		
IP Rating	IP65		
Size	124 x 130 x 100mm		
Weight	357g		

DIL SWITCH SETTINGS (SW4 N/A)					
1	2	3	Tone Description	dB Level	Current (mA)
Off	Off	Off	Sweep Negative 1200-500 Hz In 1 Second	101 (+/- 2dB)	27
On	Off	Off	Alternating 554 and 440Hz 0.5s Each	98 (+/- 2dB)	20
Off	On	Off	Continuous 660Hz	101 (+/- 2dB)	27
On	On	Off	Alternating 554Hz @ 0.1s/440Hz @ 0.4s	98 (+/- 2dB)	19
Off	Off	On	Intermittent 970Hz @ 0.5s On/Off	98 (+/- 2dB)	20
On	Off	On	Continuous 970Hz	103 (+/- 2dB)	29.3
Off	On	On	Sweep Positive 800-970Hz	103 (+/- 2dB)	38
On	On	On	Alternating 800 and 970Hz @ 0.25s Each	102 (+/- 2dB)	35