

25 Years of Manufacturing Excellence



*mkII* PROTOCOL

Standard Protocol / MKII Protocol  
Device Compatibility

# Standard Protocol / MkII Protocol Device Compatibility

In April 2013 the Zeta Alarm Systems range of Addressable fire alarm Equipment will be migrating to our new Fyreye MK II Protocol. The table below shows which devices will work with the old protocol, and which will work with the new protocol.

On the **SIMPLICITY PLUS** panel, software versions Controller **1.A - R8687** or later fully support the Fyreye MKII Protocol

To Check Software version, go to Configuration Menu 2, select Configure system, select Misc, then select Version.

|                                                                                     | Device                       | Standard Protocol         | MKII Protocol |
|-------------------------------------------------------------------------------------|------------------------------|---------------------------|---------------|
| Detectors                                                                           |                              |                           |               |
|    | FEAx2000                     | ✓                         | ✗             |
|    | FEAx2000                     | ✓                         | ✗             |
|  | MKII-Axx                     | ✗                         | ✓             |
| Interfaces                                                                          |                              |                           |               |
|  | ZIU / ZIOU / ZSCC / ZIOU/230 | ✓                         | ✗             |
|  | ZTSM                         | ✓                         | ✗             |
|  | ZTA-DH                       | ✓                         | ✗             |
|  | ZAI-MI                       | ✓<br>(Factory selectable) | ✓             |
|  | ZAI-MI                       | ✓<br>(Factory selectable) | ✓             |
|  | ZASC-MI                      | ✓<br>(Factory selectable) | ✓             |
|  | ZAZM-MI                      | ✓<br>(Factory selectable) | ✓             |

# Standard Protocol / MkII Protocol Device Compatibility

|                                                                                     | Device              | Standard Protocol      | MKII Protocol |
|-------------------------------------------------------------------------------------|---------------------|------------------------|---------------|
|    | ZIOU/I-230          | ✓                      | ✗             |
|    | ZAI0I/230           | ✗                      | ✓             |
|    | SMM/S               | ✗                      | ✓             |
|    | SMM/C               | ✗                      | ✓             |
|    | SMM/B               | ✗                      | ✓             |
| Call Points                                                                         |                     |                        |               |
|   | ZT-CP2/AD           | ✓                      | ✗             |
|  | ZT-CP3/AD           | ✓<br>(User selectable) | ✓             |
| Sounders                                                                            |                     |                        |               |
|  | ZAMD / ZAMDF        | ✓                      | ✗             |
|  | ZAMT / ZAMTF        | ✓                      | ✗             |
|  | ZAS2/xxx            | ✓                      | ✗             |
|  | ZTA-CSB / ZTA-CSFIB | ✓                      | ✗             |
|  | SM-ASB              | ✓                      | ✗             |

# Standard Protocol / MkII Protocol Device Compatibility

|                                                                                     | Device     | Standard Protocol         | MKII Protocol |
|-------------------------------------------------------------------------------------|------------|---------------------------|---------------|
|    | MKII-AMDx  | ✓<br>(User selectable)    | ✓             |
|    | MKII-AMTx  | ✓<br>(User selectable)    | ✓             |
|    | MKII-AXTx  | ✗                         | ✓             |
|    | MKII-SSB   | ✗                         | ✓             |
|    | ID2-SFB    | ✗                         | ✓             |
| Remote Indicators                                                                   |            |                           |               |
|  | ZTA-LE2    | ✓                         | ✗             |
|  | ZTA-LE3    | ✓                         | ✗             |
|  | MKII-ARL/C | ✓<br>(Factory selectable) | ✓             |
|  | MKII-ARL/W | ✓<br>(Factory selectable) | ✓             |